



Features of the Affordable Generator 6.5 KW Unit

**Programmable digital Controller / Auto Transfer and Manual switch for Standby power
Electric start / low fuel consumption / low vibration / Compact enclosure / wheels and tool
kit included / battery included/ all manuals included/ EPA Certification**

Automatic Transfer Switch and Digital Programmable controller.



**Automatic Transfer Switch
Digital Programmable Controller**



Generator Specifications Features:

- Type - Brushless type single phase
- Direct Injection Vertical, 4 cycle, air cooled
- 25.51 cubic inch displacement
- 4.3 gallon fuel tank
- Bore (3.4 in) x Stroke (2.8 in)
- Voltage - 240 VAC, 60 Hz
- Output - Rated Output 9kw
- Voltage Regulation - Equipped with Auto Voltage Regulator
- Protection - Protects against overload and short circuit
- Electric start
- 12 hour constant operation
- Amp - 45 amp 2 A
- Coupling- Direct



Includes Complete Manual and Automatic Transfer Switch

Residential 7500 Watt Transfer Kit (Components)

- 6 Circuit Box (4 x 15 AMP , 2 x 20AMP
- Nema Enclosure and Box
- 6 foot 4 wire Generator Cable
- Inlet box for Generator Receptacle
- Wire nuts (6 red , 4 yellow)
- Led Generator operating light
- Flexible Armor Cable

